EPSON®

SPC8106F0C LCD/CRT VGA Controller

BIOS Functional Specification

Document Number: X12-SP-002-05

THIS PAGE LEFT BLANK

Table of Contents

THIS PAGE LEFT BLANK

1 INTRODUCTION

1.1 Scope and Objectives

This is the Functional Specification for the SPC8104F0A BIOS. This document specifies the functions, structures and characteristics of the SPC8106F0C BIOS. It is intended for use by persons familiar with VGA BIOS functions and describes differences between the SPC8106F0C and a standard VGA BIOS. In addition this manual documents some of the behavior characteristics and structure of the BIOS.

This manual consists of several sections which include:

- Features
- Video Modes
- Main BIOS Summary
- VESA Function Summary
- SOLLEX Function Summary
- Physical layout of the BIOS
- and a series of Appendices with chip specific information

2 FEATURES

2.1 Technology

- 32 KB EPROM maximum size
- Microsoft MASM 5.1 compatible source

2.2 System and System Compatibility

- ISA machine architecture
- support for VESA VBE Core Functions version 1.2 and SOLLEX BIOS extensions
- support for VESA VBE/PM power management functions version 1.0 for BIOS version 1.14 or later
- five software power-save modes
- 3C3h or 46E8h video enable register supported (configurable)
- support for all standard IBM defined VGA modes, including modes 07h and 0Fh
- support for VESA VBE/DDC display data channel functions version 1.0 for BIOS version 1.2 or later
- selectable gray-scaling
- normal/reverse and autoswitch text/graphics of display polarity support
- autocenter support
- IRQ enable/disable support
- Selectable Cursor Blink rate
- 400 to 475 scan line expansion in text and graphics modes

2.3 Display support

- supports a variety of single/dual LCD panels of various resolutions from 320 x 200 to 640 x 480, based on MD line inputs
- supports CRT with External RAMDAC attached

2.4 Video Modes

2.4.1 LCD Display Modes

Mode No.	Mode Type	Font	Characters	Resolution	Displayed Pixels	Gray Shades	Colors	Memory Segment
0	Text	8 x 8	40 x 25	320 x 200	640 x 400	16	16	B800
0+	Text	8 x 14	40 x 25	320 x 350	640 x 350	16	16	B800
0++	Text	8 x 16	40 x 25	320 x 400	640 x 400	16	16	B800
1	Text	8 x 8	40 x 25	320 x 200	640 x 400	16	16	B800
1+	Text	8 x 14	40 x 25	320 x 350	640 x 350	16	16	B800
1++	Text	8 x 16	40 x 25	320 x 400	640 x 400	16	16	B800
2	Text	8 x 8	80 x 25	640 x 200	640 x 400	16	16	B800
2+	Text	8 x 14	80 x 25	640 x 350	640 x 350	16	16	B800
2++	Text	8 x 16	80 x 25	640 x 400	640 x 400	16	16	B800
3	Text	8 x 8	80 x 25	640 x 200	640 x 400	16	16	B800
3+	Text	8 x 14	80 x 25	640 x 350	640 x 350	16	16	B800
3++	Text	8 x 16	80 x 25	640 x 400	640 x 400	16	16	B800
4	Graphics	N/A	N/A	320 x 200	640 x 400	4	4	B800
5	Graphics	N/A	N/A	320 x 200	640 x 400	4	4	B800
6	Graphics	N/A	N/A	640 x 200	640 x 400	2	2	B800
7	Text	8 x 14	80 x 25	640 x 350	640 x 350	2	2	B000
7+	Text	8 x 16	80 x 25	640 x 400	640 x 400	2	2	B000
0D	Graphics	N/A	N/A	320 x 200	640 x 400	16	16	A000
0E	Graphics	N/A	N/A	640 x 200	640 x 400	16	16	A000
0F	Graphics	N/A	N/A	640 x 350	640 x 350	2	2	A000
10	Graphics	N/A	N/A	640 x 350	640 x 350	16	16	A000
11	Graphics	N/A	N/A	640 x 480	640 x 480	2	2	A000
12	Graphics	N/A	N/A	640 x 480	640 x 480	16	16	A000
13	Graphics	N/A	N/A	320 x 200	640 x 400	64	256	A000
100	Graphics	N/A	N/A	640 x 400	640 x 400	64	256	A000
101	Graphics	N/A	N/A	640 x 480	640 x 480	64	256	A000
108	Text	8 x 8	80 x 60	640 x 480	640 x 480	16	16	B800

2.4.2 CRT Display Modes

Mode No.	Mode Type	Font	Characters	Resolution	Displayed Pixels	Colors	Memory Segment
0	Text	8 x 8	40 x 25	320 x 200	640 x 400	16	B800
0+	Text	8 x 14	40 x 25	320 x 350	640 x 350	16	B800
0++	Text	9 x 16	40 x 25	360 x 400	720 x 400	16	B800
1	Text	8 x 8	40 x 25	320 x 200	640 x 400	16	B800
1+	Text	8 x 14	40 x 25	320 x 350	640 x 350	16	B800
1++	Text	9 x 16	40 x 25	360 x 400	720 x 400	16	B800
2	Text	8 x 8	80 x 25	640 x 200	640 x 400	16	B800
2+	Text	8 x 14	80 x 25	640 x 350	640 x 350	16	B800
2++	Text	9 x 16	80 x 25	720 x 400	640 x 400	16	B800
3	Text	8 x 8	80 x 25	640 x 200	640 x 400	16	B800
3+	Text	8 x 14	80 x 25	640 x 350	640 x 350	16	B800
3++	Text	9 x 16	80 x 25	720 x 400	640 x 400	16	B800
4	Graphics	N/A	N/A	320 x 200	640 x 400	4	B800
5	Graphics	N/A	N/A	320 x 200	640 x 400	4	B800
6	Graphics	N/A	N/A	640 x 200	640 x 400	2	B800
7	Text	8 x 14	80 x 25	640 x 350	640 x 350	2	B000
7+	Text	9 x 16	80 x 25	720 x 400	720 x 400	2	B000
0D	Graphics	N/A	N/A	320 x 200	640 x 400	16	A000
0E	Graphics	N/A	N/A	640 x 200	640 x 400	16	A000
0F	Graphics	N/A	N/A	640 x 350	640 x 350	2	A000
10	Graphics	N/A	N/A	640 x 350	640 x 350	16	A000
11	Graphics	N/A	N/A	640 x 480	640 x 480	2	A000
12	Graphics	N/A	N/A	640 x 480	640 x 480	16	A000
13	Graphics	N/A	N/A	320 x 200	640 x 400	256	A000
100	Graphics	N/A	N/A	640 x 400	640 x 400	256	A000
101	Graphics	N/A	N/A	640 x 480	640 x 480	256	A000
108	Text	8 x 8	80 x 60	640 x 480	640 x 480	16	B800

2.5 Simultaneous Display Support

Simultaneous Display is a feature in the SPC8106F0C that allows simultaneous display of both the CRT and LCD panel. Refer to the following table for supported video modes and limitations.

Note
Simultaneous Display is not supported when using a Dual panel / Dual drive LCD.

Note
All non-480 line modes (when using a 480 line panel) will show a wrap-around effect if Simultaneous Display is enabled. For example: display a 400 line mode on a 480 line panel and enable Simultaneous Display. You would see the top 78 lines duplicated on the bottom 78 lines (wrap-around affect).

Note
If using a panel with less than 480 vertical lines, Simultaneous Display will be supported, however, the maximum LCD frame-rate may be violated. Therefore, the specific panel should be referenced.

Note
If supporting a TFT panel requiring CRT-like timing (AUX[00] bit 5=1 and AUX[0B] bit 1=1) the panel handles the 350, 400 and 480 line modes, providing screen positioning internally. As the result of this direct support, Simultaneous Display is supported for all standard VGA and some extended modes.

If supporting a TFT panel requiring LCD-like timing (AUX[00] bit 5=1 and AUX[0B] bit 1=0) the Simultaneous Display mode is not supported.

Mode No.	Single Panel (640x480)	TFT - Color 9/12-bit (640x480) AUX[00] bit 5=1 AUX[0B] bit 1=1
0	No	Yes
0+	No	Yes
0++	No	Yes
1	No	Yes
1+	No	Yes
1++	No	Yes
2	No	Yes
2+	No	Yes
2++	No	Yes
3	No	Yes
3+	No	Yes
3++	No	Yes
4	No	Yes
5	No	Yes
6	No	Yes
7	No	Yes
7+	No	Yes
0D	No	Yes
0E	No	Yes
0F	No	Yes
10	No	Yes
11	Yes	Yes
12	Yes	Yes
13	No	Yes
100	No	Yes
101	Yes	Yes
108	Yes	Yes

3 OVERVIEW DESCRIPTION

The SPC8106F0C is a single chip 5 Volt LCD/CRT video controller based on VGA architecture and optimized for driving an LCD panel display. VGA standard mode functionality is supported using standard IBM VGA parameters. A proprietary 256 x 6-bit gray-scale lookup table is provided to allow remapping of the 64 possible gray shades displayed on a monochrome LCD panel. A 256 x 12-bit lookup table (4 bits per primary) provides 256 out of a possible 4096 colors on a color LCD panel.

The target market for this device is notebook computers, or other specialized consumer products. The ability to run all VGA software on a 640x480 LCD panel display is the major design consideration, therefore the BIOS must perform the same functions that the IBM VGA BIOS performs within the limitations of the SPC8106F0C.

The BIOS is divided into 3 major sections: the main BIOS, the VESA Extensions and the Sollex Extensions. It requires 32 KB of EPROM space, decoded by the system board.

3.1 Main BIOS

The main BIOS contains the core VGA compatible information. It requires 24 KB of the total 32 KB of EPROM space. This main BIOS is responsible for the initialization of the chip and for performing the IBM compatible function calls. It contains the Video Parameter Tables and the Character Tables.

3.2 VESA Extensions

The VESA Extensions are found in the last 8 KB of the 32 KB. This contains the VESA compatible functions as defined by the Video Electronics Standards Association. At time of printing the BIOS conforms to the Video BIOS Extensions Standard 1.2. These VESA functions are responsible for setting non-IBM modes and supplying functions for mode information. More information on VESA can be obtained by contacting the Video Electronics Standards Association located in San Jose, CA.

3.3 Sollex Extensions

The Sollex Extensions are defined by Seiko Epson Corporation to augment the functionality of the BIOS to include panel and power down functions. This also resides in the last 8 KB. More information on Sollex can be found in the *SOLLEX Specification* Drawing Office No. S03-SP-001-xx.

4 MAIN BIOS FUNCTION SUMMARY

4.1 Supported BIOS Functions

These functions are the IBM defined functions that are supported on all VGA compatible products. These functions are supported in the SPC8106F0C BIOS with the noted exceptions. These functions are called using the standard INT 10h interface. To call these functions:

```
MOV AH, function number
MOV other register, other parameters
INT 10H
```

Function 00h - Set Video Mode

```
Input:     AH=00h    Set Video Mode
           AL        Video mode (bit 7 set prevents VRAM c lear)
Return:    n/a
```

Function 01h - Set Cursor Type

```
Input:     AH=01h    Set Cursor Type
           CH        Cursor start scan
           CL        Cursor end scan
Return:    n/a
```

Function 02h - Set Cursor Position

```
Input:     AH=02h    Set Cursor Position
           BH        Page number
           DL        Column (0-x)
           DH        Row (0-x)
Return:    n/a
Destroyed: AX,SI
```

Function 03h - Read Cursor Position

```
Input:     AH=03h    Read Cursor Position
           BH        Page number
Return:    CX        Current cursor mode
           DX        Current cursor position
```

Function 04h - Read Lightpen Position (Unsupported On VGA)

```
Input:     AH=04h    Read Lightpen Position
Return:    AH        Lightpen status (0=none, 1=active)
                     If AH=1 then:
                              BX - Pixel column
                              CX - Scan line
                              DX - Character row/column
```

Function 05h - Select Active Display Page

```
Input:      AH=05h    Select Active Display Page
            AL        New page number
Return:     n/a
```

Function 06h - Scroll Active Page Up

```
Input:      AH=06h    Scroll Active Page Up
            AL        Lines to scroll (0=blank window)
            BH        New line(s) attribute
            CX        Top-left corner of scroll window
            DX        Bottom-right corner of scroll window
Return:     n/a
Destroyed:  AX, SI, DI, (and DS if text modes)
```

Function 07h - Scroll Active Page Down

```
Input:      AH=07h    Scroll Active Page Down
            AL        Lines to scroll (0=blank window)
            BH        New line(s) attribute
            CX        Top-left corner of scroll window
            DX        Bottom-right corner of scroll window
Return:     n/a
```

Function 08h - Read Character/attribute at Cursor Position

```
Input:      AH=08h    Read Character/attribute at Cursor Posit ion
            BH        Page number
Return:     AL        Character read
            AH        Attribute read
Destroyed:  AX, SI, DI, (and DS if text modes)
```

Function 09h - Write Character/attribute at Cursor Position

```
Input:      AH=09h    Write Character/attribute at Cursor Posi tion
            AL        Character to write
            BL        Character attribute/color (b7 set for  XOR)
            BH        Page number (Background color in Mode  13)
            CX        Character count
Return:     n/a
Destroyed:  AX, SI, DI, (and DS if text modes)
```

Function 0Ah - Write Character Only at Cursor Position

```
Input:      AH=0Ah    Write Character only at Cursor Position
            AL        Character to write
            BH        Page number
            CX        Character count
Return:     n/a
Destroyed:  AX, SI, DI, (and DS if text modes)
```

Function 0Bh - Set Color Palette

```
Input:      AH=0Bh    Set Color Palette
            BH=0      (selects background color)
                      BL=0-Fh   Background color
            BH=1      (selects palette)
                      BL=0      (Green, Red, Brown)
                      BL=1      (Cyan, Magenta, White)
Return:     n/a
```

Function 0Ch - Write Dot

```
Input:      AH=0Ch    Write Dot
            AL        Color (b7 set for XOR)
            BH        Page number
            CX        Column
            DX        Row
Return:     n/a
```

Function 0Dh - Read Dot

```
Input:      AH=0Dh    Read Dot
            BH        Page number
            CX        Column
            DX        Row
Return:     AL        Dot color
```

Function 0Eh - Write TTY Character to Active Page

```
Input:      AH=0Eh    Write TTY Character to Active Page
            AL        Character (CR, LF, BS, and BELL accep ted)
            BL        Color in graphics mode
Return:     n/a
```

Function 0Fh - Get Current Video State

```
Input:      AH=0Fh    Get Current Video State
Return:     AL        Current video mode
            AH        Number of columns
            BH        Current page number
```

Function 10h - Palette Functions

```
Input:    AH=10h    Palette Functions
          AL=00     Set palette register
          BL        Palette register
          BH        Value to be set
Return:   n/a

Input:    AH=10h    Palette Functions
          AL=01     Set overscan register
          BH        Value to be set
Return:   n/a

Input:    AH=10h    Palette Functions
          AL=02     Set all palette registers and overscan
          ES:DX     Pointer to 17-byte table
Return:   n/a

Input:    AH=10h    Palette Functions
          AL=03     Toggle intensity/blink bit
          BL        1=Blink, 0=Intensity
Return:   n/a

Input:    AH=10h    Palette Functions
          AL=07     Get palette register
          BL        Palette register
Return:   BH        Palette register value

Input:    AH=10h    Palette Functions
          AL=08     Get overscan register
Return:   BH        Overscan register value

Input:    AH=10h    Palette Functions
          AL=09     Get all palette registers and overscan
          ES:DX     Pointer to 17-byte table
Return:   n/a

Input:    AH=10h    Palette Functions
          AL=10h    Set DAC color register
          BX        Color register
          DH:CH:CL  Red, Green, Blue data
Return:   n/a
```

```
Input:    AH=10h   Palette Functions
          AL=12h   Set block of DAC registers
          BX       Start color register
          CX       Number of registers
          ES:DX    Pointer to RGB table
Return:   n/a

Input:    AH=10h   Palette Functions
          AL=13h   Select color page
          BL       Paging function (0-1)
                   00       Select paging mode
                   01       Select page
          BH       If BL=0 (0=4 of 64, 1=16 of 16)
                   If BL=1 (Page number 0-3, 0-15)
Return:   n/a

Input:    AH=10h   Palette Functions
          AL=15h   Get DAC color register
          BX       Color register
Return:   DH       Red value
          CH       Green value
          CL       Blue value

Input:    AH=10h   Palette Functions
          AL=17h   Get block of DAC registers
          BX       Start color register
          CX       Number of registers
          ES:DX    Pointer to RGB table
Return:   n/a

Input:    AH=10h   Palette Functions
          AL=18h   Set PEL Mask (VGA Undocumented)
          BL       PEL Mask to write
Return:   n/a

Input:    AH=10h   Palette Functions
          AL=19h   Get PEL Mask (VGA Undocumented!)
          BX       Returned PEL Mask value
Return:   n/a

Input:    AH=10h   Palette Functions
          AL=1Ah   Get current color page
          BL       Returned paging mode
          BH       Returned page number
Return:   n/a
```

```
Input:    AH=10h   Palette Functions
          AL=1Bh   Convert all DAC registers to gray-scale
          BX       Start color register
          CX       Number of registers
Return:   n/a
```

Note
Overscan Subfunction 01 incorrectly puts the data into the parameter save area offset + 11h to be consistent with IBM code.

Function 11h - Character Generator Control

```
          AL              Character generator function (0-30h)
                          0x - Alpha load (x=0-4)
                          1x - Alpha load, recalculated (x=0-2, 4)
                          2x - Graphics load (x=0-4)
                          30 - Return information

Input:    AH=11h   Character generator function
          AL=00 or AL=10h (user alpha load):
          BL       Block to load
          BH       Points
          CX       Character count
          DX       Character offset
          ES:BP    Font table pointer
Return:   n/a

Input:    AH=11h   Character generator function
          AL=01 or AL=11h (ROM 8x14 set):
          BL       Block to load
Return:   n/a

Input:    AH=11h   Character generator function
          AL=02 or AL=12h (ROM 8x8 set):
          BL       Block to load
Return:   n/a

Input:    AH=11h   Character generator function
          AL=04 or AL=14h (ROM 8x16 set):
          BL       Block to load
Return:   n/a

Input:    AH=11h   Character generator function
          AL=03    (set active block):
          BL       Value for sequencer register 3
Return:   n/a
```

```
Input:    AH=11h   Character generator function
          AL=20h    (user graphics characters):
          ES:BP    Font table pointer (chars 128-255)
Return:   n/a

Input:    AH=11h   Character generator function
          AL=21h    (user graphics load):
          BL       Rows select (0=user, 1=14, 2=25, 3=43 )
          CX       Points
          DL       Rows Input: BL=0
          ES:BP    Font table pointer
Return:   n/a

Input:    AH=11h   Character generator function
          AL=22h    (ROM 8x14 set):
          BL       Rows select
Return:   n/a

Input:    AH=11h   Character generator function
          AL=23h    (ROM 8x8 set):
          BL       Rows select
Return:   n/a

Input:    AH=11h   Character generator function
          AL=24h    (ROM 8x16 set):
          BL       Rows select
Return:   n/a

Input:    AH=11h   Character generator function
          AL=30h    (return information):
          BH       Function request (0-7)
                   0 - Get INT 1F pointer
                   1 - Get INT 43 pointer
                   2 - Get ROM 8x14 pointer
                   3 - Get ROM 8x8 pointer
                   4 - Get ROM 8x8 pointer (128-255)
                   5 - Get 9x14 fudge table pointer
                   6 - Get ROM 8x16 pointer
                   7 - Get 9x16 fudge table pointer
                   (fudge font never used, but
                   point size returned should be valid)
Return:   CX       Points
          DL       Rows
          ES:BP    Table pointer
```

Function 12h - Miscellaneous Functions

```
Input:    AH=12h   Miscellaneous Function
          BL=10h   Return EGA information
Return:   BL       Memory (0=64K, 1=128K, 2=192K, 3=256K)
          BH       0 = color mode active, 1 = mono mode  active
          CL       Switch settings
          CH       Feature bits

Input:    AH=12h   Miscellaneous Function
          BL=20h   Select EGA print screen routine
Return:   n/a

Input:    AH=12h   Miscellaneous Function
          AL=30h   Set alpha mode scan count
          AL       0=200, 1=350, 2=400 scans
Return:   AL=12h

Input:    AH=12h   Miscellaneous Function
          BL=31h   Palette load on mode set
          AL       0=enable, 1=disable
Return:   AL=12h

Input:    AH=12h   Miscellaneous Function
          BL=32h   Video control
          AL       0=enable, 1=disable
Return:   AL=12h

Input:    AH=12h   Miscellaneous Function
          BL=33h   gray-scale summing
          AL       0=enable, 1=disable
Return:   AL=12h

Input:    AH=12h   Miscellaneous Function
          BL=34h   Cursor emulation control
          AL       0=enable, 1=disable
Return:   AL=12h

Input:    AH=12h   Miscellaneous Function
          BL=35h   Display control
          AL       Function request
                   00 - Adapter off (initial)
                   01 - Planar on (initial)
                   02 - Active off
                   03 - Inactive on
                   ES:DX    Pointer to 128-byte buffer
```

```
Return:    n/a

Input:     AH=12h    Miscellaneous Function
           BL=36h    Video data control
           AL        0=enable, 1=disable
Return:    AL=12h
```

Function 13h - Write String Functions

```
Input:     AH=13h    Write String function
           AL        String function
                     0 - BL=attribute, string=char, char,...
                     1 - BL=attribute, string=char, char, ... cursor moved
                     2 - String=char, attr, char, attr...
                     3 - String=char, attr, char, attr ... cursor mov ed
           BL        Attribute (if AL=0 or 1)
           BH        Page number
           CX        Character count
           DX        Start cursor position
           ES:BP     String pointer
Return:    n/a
```

Note
If any scrolling occurs, the active page will be scrolled, not the requested page! This "feature" is also present in IBM's code and it has been determined that it is better to reproduce this in our code for compatibility.

Function 14h To Function 19h - Null Functions

Functions 14h to 19h are reserved by VGA definition. Any requests of these functions will just simply return and nothing happens.

```
Input:     n/a
Return:    n/a
```

Function 1Ah - Read/Write Display Combination Code

```
Input:     AH=1Ah    Read/write Display Combination Code
           AL        0=read, 1=write
           BL        Active DCC (r/w)
           BH        Alternate DCC (r/w)
Return:    AL=1Ah
           BX        Set as above
```

Function 1Bh - Return Functionality/State Information

```
Input:      AH=1Bh    Return Functionality/State Information
            BX        Implementation type (must be 00)
            ES:DI     Pointer to buffer
Return:     AL=1Bh
            ES:DI     Contains information
```

The format of the information block is as follows:

Offset	Type	Description
00	DD	Pointer to static functionality table
04	DB	CRT video mode
05	DW	CRT columns
07	DW	VRAM page length
09	DW	VRAM start address
0B 8h x DW		Cursor row/column for 8 pages
1B	DW	Cursor type
1D	DB	Active page
1E	DW	CRTC address
20	DB	Port 3D8 data
21	DB	Port 3D9 data
22	DB	Number of rows
23	DW	Point size
25	DB	Active DCC
26	DB	Auxiliary DCC
27	DW	Number of colors this mode
29	DB	Number of pages this mode
2A	DB	Number of scans this mode (0=200 1=350 2=400 3=480)
2B	DB	Primary character block
2C	DB	Secondary character block
2D	DB	Misc. state info (see table below)
2E 3h x DB		Reserved (set to zero)
31	DB	VRAM size (0=64K 1=128K 2=192K 3=256K)
32	DB	Save pointer state info (see table below)
33 Dh x DB		Reserved (set to zero)

These are values directly copied from low memory.

Table 4-1 Information Block Offset 2D



Table 4-2 Information Block Offset 32



Function 1Ch - Save/Restore Video State

```
Input:      AH=1Ch    Save/Restore Video State
            AL        Function request (0-2)
                      00 - Return size of buffer
                      01 - Save video state
                      02 - Restore video state
            ES:BX     Pointer to buffer
            CX        Bit map of request
                      001 - Video h/w status
                      010 - Video data arena
                      100 - Video DAC and color registers
Return:     AL=1Ch
            BX        Buffer size if AL input =00
```

Note
Emulating IBM code this function does not save the latch data or color select register 14h of the Attributes Controller. Because it doesn't get saved or restored, we don't touch it at all.

The format of the save buffer is as follows:

Offsets

```
00h          DW       Offset to the Video Hardware Statu s buffer
02h          DW       Offset to the Video Data Arena buf fer
04h          DW       Offset to the DAC and Color Regist ers buffer
06h 0Dh x DW          Reserved (uninitialized)
```

Video Hardware Status

```
00h          DB        Sequencer (3C4) index
01h          DB        CRTC (3D4) index
02h          DB        Graphics controller (3CE) index
03h          DB        Attributes controller (3C0) index
04h          DB        Feature control register (3DA) dat a
05h 4h x DB            Sequencer data
09h          DB        Misc. output register (3C2) data
0Ah 19h x DB           CRTC data
23h 14h x DB           Attributes controller data
37h 9h x DB            Graphics controller data
40h          DW        CRTC base port
42h 4h x DB            Latch data
```

Video Data Arena

```
00h          DB        EquipLow AND 30h
01h          DB        CRTMode
02h          DW        CRTColumns
04h          DW        VRAMPageLength
06h          DW        VRAMStartAddr
08h  8h x DW           CursorRowCol
18h          DW        CursorType
1Ah          DB        ActivePage
1Bh          DW        CRTCAddr
1Dh          DB        Port3D8Data
1Eh          DB        Port3D9Data
1Fh          DB        MaxRow
0h           DW        Points
22h          DB        EGAInfo
23h          DB        DIPInfo
24h          DB        VGAInfo
25h          DB        DCCIndex
26h          DD        SavePtr
2Ah          DD        Vec05
2Eh          DD        Vec1D
32h          DD        Vec1F
36h          DD        Vec43
```

DAC and Color Registers

```
00h          DB        DAC state (3C7) AND 01h (1=read mo de, 0=write mode)
01h          DB        DAC (3C8) index (adjusted)
02h          DB        Pel mask (3C6) data
03h 300h x DB          DAC RGB data
```

5 VESA VBE FUNCTION SUMMARY

These functions are defined by the Video Electronics Standards Association. They cover issues of inquiry on chip capability, and available modes. The following section shows the SPC8106F0C implementation of these functions. The SPC8106F0C BIOS supports VESA VBE Core functions 1.2, VBE/PM functions 1.0 and VBE/DDC function 1.0. BIOS version 2.0 will support VBE Core functions 2.0.

5.1 Status Information

Every function returns status information in the AX register. The format of the status word is as follows:

```
AL ==   4Fh:    Function is supported
AL !=   4Fh:    Function is not supported
AH ==   00h:    Function call successful
AH ==   01h:    Function call failed
AH ==   02h:    Software supports this function, but the hardware
                does not
AH ==   03h:    Function call invalid in current video mode
```

5.2 VESA Functions

Function 00h - Return VBE Controller Information

```
Input:  AX      = 4F00h  Return VBE Controller Information
        ES:DI   =        Pointer to buffer in which to place VbeInfoBlock
                         structure (VbeSignature should be set to 'VBE2' when
                         function is called to indicate VBE 2.0 information is
                         desired and the information block is 512 bytes in
                         size.)
Return: AX      =        VBE Return Status
```

Note
All other registers are preserved.

Function 01h - Return VBE Mode Information

```
Input:  AX      = 4F01h  Return VBE mode information
        CX      =        Mode number
        ES:DI   =        Pointer to ModeInfoBlock structure

Return: AX      =        VBE Return Status
```

Note
All other registers are preserved.

Function 02h - Set VBE Mode

```
Input:   AX      = 4F02h  Set VBE Mode
         BX      =        Desired Mode to set
                          D0-D8 = Mode number
                          D9-D13 = Reserved (must be 0)
                          D14 = 0 Use windowed frame buffer model
                              = 1 Use linear/flat frame buffer model
                          D15 = 0 Clear display memory
                              = 1 Don't clear display memory
Return:  AX      =        VBE Return Status
```

Note
All other registers are preserved.

Function 03h - Return current VBE Mode

```
Input:   AX      = 4F03h  Return current VBE Mode
Return:  AX      =        VBE Return Status
         BX      =        Current VBE mode
                          D0-D13 = Mode number
                          D14 = 0 Windowed frame buffer model
                              = 1 Linear/flat frame buffer model
                          D15 = 0 Memory cleared at last mode set
                              = 1 Memory not cleared at last mode set
```

Note
All other registers are preserved.

Function 04h - Save/Restore state

```
Input:   AX      =        4F04h Save/Restore state
         DL      =        00h Return save/restore state buffer size
                 =        01h Save state
                 =        02h Restore state
         CX      =        Requested states
                 D0 =     Save/restore controller hardware state
                 D1=      Save/restore BIOS data state
                 D2=      Save/restore DAC state
                 D3=      Save/restore Register state
         ES:BX   =        Pointer to buffer (if DL <> 00h)
Return:  AX      =        VBE Return Status
         BX      =        Number of 64-byte blocks to hold the state buffer (if
                          DL=00h)
```

Note
All other registers are preserved.

Function 05h - Display Window Control

Input:	AX	= 4F05h	VBE Display Window Control
	BH	= 00h	Set memory window
		= 01h	Get memory window
	BL	=	Window number
		= 00h	Window A
		= 01h	Window B
	DX	=	Window number in video memory in window granularity units (Set Memory Window only)
Return:	AX	=	VBE Return Status
	DX	=	Window number in window granularity units (Get Memory Window only)

Function 06h - Set/Get Logical Scan Line Length

Input:	AX	= 4F06h	VBE Set/Get Logical Scan Line Length
	BL	= 00h	Set Scan Line Length in Pixels
		= 01h	Get Scan Line Length
		= 02h	Set Scan Line Length in Bytes
		= 03h	Get Maximum Scan Line Length
	CX	=	If BL=00h Desired Width in Pixels If BL=02h Desired Width in Bytes (Ignored for Get Functions)
Return:	AX	=	VBE Return Status
	BX	=	Bytes Per Scan Line
	CX	=	Actual Pixels Per Scan Line (truncated to nearest complete pixel)
	DX	=	Maximum Number of Scan Lines

Function 07h - Set/Get Display Start

Input:	AX	= 4F07h	VBE Set/Get Display Start Control
	BH	= 00h	Reserved and must be 00h
	BL	= 00h	Set Display Start
		= 01h	Get Display Start
		= 80h	Set Display Start during Vertical Retrace
	CX	=	First Displayed Pixel In Scan Line (Set Display Start only)
	DX	=	First Displayed Scan Line (Set Display Start only)
Return:	AX	=	VBE Return Status
	BH	=	00h Reserved and will be 0 (Get Display Start only)
	CX	=	First Displayed Pixel In Scan Line (Get Display Start only
	DX	=	First Displayed Scan Line (Get Display Start only)

Function 08h - Set/Get DAC Palette Format

```
Input:   AX      = 4F08h  VBE Set/Get Palette Format
         BL      = 00h    Set DAC Palette Format
                 = 01h    Get DAC Palette Format
         BH      =        Desired bits of color per primary
                          (Set DAC Palette Format only)
Return:  AX      =        VBE Return Status
         BH      =        Current number of bits of color per primary
```

Function 09h - Set/Get Palette Data

```
Input:   AX      = 4F09h  VBE Load/Unload Palette Data
         BL      = 00h    Set Palette Data
                 = 01h    Get Palette Data
                 = 02h    Set Secondary Palette Data
                 = 03h    Get Secondary Palette Data
                 = 80h    Set Palette Data during Vertical Retrace  with Blank
                          Bit on
         CX      =        Number of palette registers to update
         DX      =        First palette register to update
         ES:DI   =        Table of palette values (see below for format)
Return:  AX      =        VBE Return Status
```

Format of Palette Values: Alignment byte, Red byte, Green byte, Blue byte

Function 0Ah - Return VBE Protected Mode Interface

```
Input:   AX      = 4F0Bh  VBE 2.0 Protected Mode Interface
         BL      = 00h    Return protected mode table
Return:  AX      =        Status
         ES      =        Real Mode Segment of Table
         DI      =        Offset of Table
         CX      =        Length of Table including protected mode code
                          (for copying purposes)
```

The format of the table is as follows:

```
ES:DI + 00h      Word Offset in table of Protected mode code for
                 Function 5 for Set Window Call
ES:DI + 02h      Word Offset in table of Protected mode code for
                 Function 7 for set Display Start
ES:DI + 04h      Word Offset in table of Protected mode code for
                 Function 9 for set Primary Palette data
ES:DI + 06h      Word Offset in table of Ports and Memory Locations
                 that the application may need I/O privilege for.
                 (Optional: if unsupported this must be 0000h)
                 (See Sub-table for format)
ES:DI + ?        Variable remainder of Table including Code
```

Function 10h - Display Power Management Extensions
(valid for BIOS version 1.2 or greater)

The VESA VBE sub-Function 10h is used to implement the VBE / PM services. The VBE / PM services are defined as follows:

Sub-Function 00h - Report VBE / PM Capabilities

```
Input:   AH      = 4Fh    VESA Extension.
         AL      = 10h    VBE/PM Services.
         BL      = 00h    Report VBE/PM Capabilities.
         CX      = 00h    Controller unit number (00 = primary controller).
         ES:DI            Null pointer, must be 0000:0000h in version 1.0.
                          Reserved for future use.
Return:  AX      =        Status.
         BH      =        Power saving state signals supported by the
                          controller. 1 = supported, 2 = not supported
                          bit 0 STANDBY
                          bit 1 SUSPEND
                          bit 2 OFF
                          bit 3 REDUCED ON
                          bits 4-7 reserved for future power control of the
                                   display controller or other related
                                   circuits.
         BL      =        VBE/PM version number (0001 0000b for this versio n).
                          bits 0-3 minor version number
                          bits 4-7 major version number
         CX      =        Unchanged
         ES:DI            Unchanged
All other registers may be destroyed.
```

Sub-Function 01h - Set Display Power State

```
Input:   AH      = 4Fh    VESA Extension.
         AL      = 10h    VBE/PM Services.
         BL      = 01h    Set Display Power State.
         BH      = 00h    ON
                 = 01h    STANDBY
                 = 02h    SUSPEND
                 = 04h    OFF
                 = 08h    REDUCED ON
                 All other BH values are currently undefined and are reserved
                 for future power control of the display controll er.
         CX      = 00h    Controller unit number (00 = primary controller).
Return:  AX      =        Status.
         BH      =        Unchanged
         CX      =        Unchanged
All other registers may be destroyed.
```

Sub-Function 02h - Get Display Power State

```
Input:   AH      = 4Fh    VESA Extension.
         AL      = 10h    VBE/PM Services.
         BL      = 02h    Get Display Power State.
         CX      = 00h    Controller unit number (00 = primary controller).
Return:  AX      =        Status.
         BH               Power state currently requested by the controller .
                 = 00h    ON
                 = 01h    STANDBY
                 = 02h    SUSPEND
                 = 04h    OFF
                 = 08h    REDUCED ON
                 All other BH values are reserved and may be used to signal
                 other power saving states in future revisions of VBE/PM. For
                 future compatibility, applications written for V BE/PM 1.0
                 should ignore the value of bits 4 to 7.
         CX      =        Unchanged
All other registers may be destroyed.
```

Function 15h - Display Identification Extensions
(valid for BIOS version 1.2 or greater)

The VESA VBE sub-Function 15h is used to implement the VBE / DDC services. The VBE / DDC services are defined as follows:

Sub-Function 00h - Report VBE / DDC Capabilities

```
Input:   AH      = 4Fh    VESA Extension.
         AL      = 15h    VBE/DDC Services.
         BL      = 00h    Report VBE/DDC Capabilities.
         CX      = 00h    Controller unit number (00 = primary controller).
         ES:DI            Null pointer, must be 0000:0000h in version 1.0.
                          Reserved for future use.
Return:  AX      =        Status
         BH      =        Approximate time, in seconds, rounded up, to transfer
                          one EDID block (128 bytes).
         BL      =        DDC level supported.
                          bit 0 = 0 DDC1 not supported
                                = 1 DDC1 supported
                          bit 1 = 0 DDC2 not supported
                                = 1 DDC2 supported
                          bit 2 = 0 screen not blanked during data transfer
                                = 1 screen blanked during data transfer
         CX      =        Unchanged
         ES:DI            Unchanged
All other registers may be destroyed.
```

Sub-Function 01h - Read EDID

Input:	AH	= 4Fh	VESA Extension.
	AL	= 15h	VBE/DDC Services.
	BL	= 01h	Read EDID.
	CX	= 00h	Controller unit number (00 = primary controller).
	DX	= 00h	EDID block number. Zero is the only valid value in version 1.0.
	ES:DI		Pointer to the area in which the EDID block (128 bytes) shall be returned.
Return:	AX	=	Status
	BH	=	Unchanged
	CX	=	Unchanged
	ES:DI		Pointer to the area in which the EDID block (128 bytes) is returned.

All other registers may be destroyed.

Sub-Function 02h - Read VDIF Block

Input:	AH	= 4Fh	VESA Extension.
	AL	= 15h	VBE/DDC Services.
	BL	= 02h	Read VDIF block.
	CX	= 00h	Controller unit number (00 = primary controller).
	DX	= 00h	VDIF block number (64 byte block).
	ES:DI		Pointer to the area in which the VDIF block (64 bytes) shall be returned.
Return:	AX	=	Status
	BH	=	Unchanged
	CX	=	Unchanged
	ES:DI		Pointer to the area in which the VDIF block (64 bytes) is returned.

All other registers may be destroyed.

6 SOLLEX FUNCTION SUMMARY

These functions are defined by Seiko Epson as a generic interface for functions not covered by the Video Electronics Standards Association or IBM's standard video BIOS. The following has been marked up to show the SPC8106F0C implementation of these functions.

6.1 Sollex Status Information

Every function returns status information in the AX register. The format of the status words is as follows:

```
AL == 7Fh:    Function is supported
AL != 7Fh:    Function is not supported
AH == 00h:    Function call successful
AH == 01h:    Function call fails
```

6.2 Sollex Reserved Bits

All reserved bit returns will return 0 by default, unless otherwise noted.

6.3 Sollex Functions

Function 00h - Return Extensions Info

Not supported in SPC8106F0C.

Function 01h - Adapter Control

```
Input:    AH=7Fh   SOLLEX Support
          AL=01h   Adapter Control
          BL=00h   Set Adapter
          CX       Adapter Request
Return:   AX       Status

Input:    AH=7Fh   SOLLEX Support
          AL=01h   Adapter Control
          BL=01h   Get Adapter
Return:   AX       Status
          BX       Adapter type
          DX       Display type

Input:    AH=7Fh   SOLLEX Support
          AL=01h   Adapter Control
          BL=02h   Return Adapter Support
          CX       Adapter Request
Return:   AX       Status
```

Table 6-1 Sub-Function 00h: Set Adapter



Table 6-2 Sub-Function 01h: Get Adapter



SubFunction 2 uses the same Adapter Request format as SubFunction 0 to determine whether the requested adapter setting could be successfully set in the current environment.

Function 02h - Display Output Control

```
Input:    AH=7Fh   SOLLEX Support
          AL=02h   Display Output Control
          BL=00h   Set Display Output
          CX       Display Setting
Return:   AX       Status

Input:    AH=7Fh   SOLLEX Support
          AL=02h   Display Output Control
          BL=01h   Get Display Output
Return:   AX       Status
          BX       Display Output
          CX       Displays attached
```

Table 6-3 Sub-Function 00h: Set Display Output



Table 6-4 Sub-Function 01h: Get Display Output



The CX register contains the following bit mask that describes the attached displays:

Table 6-5 Display Attached



Function 03h - Video Support Control

Not supported in SPC8106F0C.

Function 04h - Power Control

```
Input:    AH=7Fh    SOLLEX Support
          AL=04h    Power Control
          BL=00h    Set Power State
          CX        Power State (0 to Maximum State)
Return:   AX        Status

Input:    AH=7Fh    SOLLEX Support
          AL=04h    Power Control
          BL=01h    Get Power State
Return:   AX        Status
          CX        Power State
          DX        Maximum State

Input:    AH=7Fh    SOLLEX Support (UNSUPPORTED in SPC8106F0 C)
          AL=04h    Power Control
          BL=02h    Set Time Out Reset
          CX        Time Out Reset (0 to Maximum Time Out  Reset)
Return:   AX        Status AL=7Fh, AH=01h

Input:    AH=7Fh    SOLLEX Support (UNSUPPORTED in SPC8106F0 C)
          AL=04h    Power Control
          BL=03h    Get Time Out Reset
Return:   AX        Status AL=7Fh, AH=01h
```

SubFunction 00h: Set Power State

Set Power State according to table below.

SubFunction 01h: Get Power State

Returns Power State according to table below.

	State 0	State 1	State 2	State 3	State 4	State 5***
Clock	Yes	Yes	Yes	No	Yes*	Yes****
Display (panel) enabled	Yes	No	No	No	No	Yes
CRT display access	Yes	No	No	No	No	Yes
CPU to VRAM Refresh	Yes	Yes	No	No	No	Yes
VRAM Refresh	Yes	Yes	Yes	No	External	Yes
IO Write/IO Read	Yes	Yes	Yes	Aux Registers	Aux Registers	Yes
Ext.RamDAC	Yes	No**	No**	No	No	No
Relative Power Saving	None	Low	Medium	High	High	minimal

* can use Power Down clock if available
** read/write allowed
*** not available on CRT
**** Clock is slower by 25%

Function 05h - Load Register

Not supported in SPC8106F0C.

Function 06h - Multiple Font Control

```
Input:    AH=7Fh   SOLLEX Support
          AL=06h   Multiple Font Control
          BL=00h   Set Multiple Font State
          CX       Multiple Font State
                   0h=off
                   1h=on
Return:   AX       Status

Input:    AH=7Fh   SOLLEX Support
          AL=06h   Multiple Font Control
          BL=01h   Get Multiple Font State
Return:   AX       Status
          BL       Multiple Font State
                   0h=off
                   1h=on
```

Function 07h - Fill Video RAM

Not supported in SPC8106F0C.

Function 08h - Autocenter Control

```
Input:    AH=7Fh   SOLLEX Support
          AL=08h   Autocenter control
          BL=00h   Set Autocenter control
          CX       0000h Disable Autocenter
                   0001h Enable Autocenter
Return:   AX       Status

Input:    AH=7Fh   SOLLEX Support
          AL=08h   Autocenter control
          BL=01h   Get Autocenter state
Return:   AX       Status
          BL       Autocenter control status
                   00h=Disabled
                   01h=Enabled
```

Function 09h - Lookup Table Control

Not supported in SPC8106F0C.

Function 0Ah - Non-Standard Font Control (SPC8106F0C uses 19pt.font for h/w text expansion*)

```
Input:    AH=7Fh    SOLLEX Support
          AL=0Ah    Non-Standard Font Control
          BL=00h    Set Non-Standard Font Control state
          CL        Font Width
          CH        Font Height (if CX=0, it will set nor mal system
                    font to be default)
Return:   AX        Status

Input:    AH=7Fh    SOLLEX Support
          AL=0Ah    Non-Standard Font Control
          BL=01h    Get Non-Standard Font Control state
Return:   AX=       Status
          BL=       Font Width
          BH=       Font Height (normal system font will  return proper
                    values not 0 as in the set)
          ES:DI     pointer to table of available fonts
                    (format width, height, width, height ... 00, 00)
```

* use 19 point for set to enable Hardware Text Expansion

Function FFh - Chip Specific Function

```
Input:    AH=7Fh   SOLLEX Support
          AL=FFh   Chip Specific Function
          BL=00h   Set
          CX       Requested State
          DH       Graphic expansion line number (if D8  of CX is 1)
Return:   AX       Status

Input:    AH=7Fh   SOLLEX Support
          AL=FFh   Chip Specific Function
          BL=01h   Get
Return:   AX=      Status
          BH=      Chip Revision Product Code
          BL=      Chip Revision
          CX=      Current State
          DH=      Graphic expansion line number (if D8  of CX is 1)
```

Table 6-6 Chip Specific Function



7 PHYSICAL LAYOUT OF THE BIOS

7.1 Single Segment Structure

The BIOS will exist in a 32 KB section of ROM located at C000 or any other configurable location. Segment references within the code will self define at initialization time, however an initial BIOS segment must be configured into the ROM image.

The layout of this segment is as follows:

Initialization Routine	Function Dispatch	Function Calls	Video Parameter Table	Character Fonts 8, 14, 16, & 18 or 19 if needed	Extensions Initialization	Extensions Dispatch	Extensions Function Calls	Extensions Parameter Tables

The single segment structure of the BIOS versus a dual image structure (where the Extensions have their own segment) has the advantage that OS/2 2.0 will work correctly in the virtual DOS box.

7.2 IBM Notice, Copyright Notice

Some software expects the word 'IBM' to be located at C000:001E to determine if it is running on an EGA or better. We have initially put the word 'IBM' at this location, but, if the BIOS is relocated to another segment, E000 for example, software that does check at C000:001E will not work. There is very little chance of running across current software with this test.

The BIOS will also contain the string "Copyright (c) Seiko Epson Corp. 1987, 1993. All rights reserved" in two locations. One of these must stay in the code, the other is part of the header that is displayed on power-up. The power-up string is configurable and can be overwritten by the OEM.